

## Full Adder Circuit. Part II

Grzegorz Bancerek  
Białystok Technical University

Shin'nosuke Yamaguchi  
Shinshu University  
Nagano

Katsumi Wasaki  
Shinshu University  
Nagano

**Summary.** In this article we continue the investigations from [5] of verification of a design of adder circuit. We define it as a combination of 1-bit adders using schemes from [6].  $n$ -bit adder circuit has the following structure

$x_1 \ y_1$                        $x_2 \ y_2$      $x_n \ y_n$

1st	2nd	nth
bit	bit	bit
adder	adder	adder

As the main result we prove the stability <sup>$r_1$</sup>  of the circuit. Further works will consist of the proof of full correctness <sup>$r_2$</sup>  of the circuit.  <sup>$r_n$</sup>

MML Identifier: FACIRC\_2.

WWW: [http://mizar.org/JFM/Vol14/facirc\\_2.html](http://mizar.org/JFM/Vol14/facirc_2.html)

The articles [17], [16], [22], [21], [2], [18], [23], [1], [7], [8], [4], [10], [11], [3], [19], [24], [15], [9], [20], [13], [14], [12], and [5] provide the notation and terminology for this paper.

One can prove the following propositions:

(1) For all sets  $x, y, z$  such that  $x \neq z$  and  $y \neq z$  holds  $\{x, y\} \setminus \{z\} = \{x, y\}$ .

(3)<sup>1</sup> For all sets  $x, y, z$  holds  $x \neq \langle \langle x, y \rangle, z \rangle$  and  $y \neq \langle \langle x, y \rangle, z \rangle$ .

Let us observe that every many sorted signature which is void is also unsplit and has arity held in gates and Boolean denotation held in gates.

One can verify that there exists a many sorted signature which is strict and void.

Let  $x$  be a set. The functor  $\text{SingleMSS } x$  yielding a strict void many sorted signature is defined as follows:

<sup>1</sup> The proposition (2) has been removed.

(Def. 1) The carrier of  $\text{SingleMSS } x = \{x\}$ .

Let  $x$  be a set. One can check that  $\text{SingleMSS } x$  is non empty.

Let  $x$  be a set.

(Def. 2)  $\text{SingleMSA } x$  is a Boolean strict algebra over  $\text{SingleMSS } x$ .

Next we state three propositions:

(4) For every set  $x$  and for every many sorted signature  $S$  holds  $\text{SingleMSS } x \approx S$ .

(5) Let  $x$  be a set and  $S$  be a non empty many sorted signature. Suppose  $x \in$  the carrier of  $S$ . Then  $\text{SingleMSS } x + S =$  the many sorted signature of  $S$ .

(6) Let  $x$  be a set,  $S$  be a non empty strict many sorted signature, and  $A$  be a Boolean algebra over  $S$ . If  $x \in$  the carrier of  $S$ , then  $\text{SingleMSA } x + A =$  the algebra of  $A$ .

$\emptyset$  is a finite sequence with length 0. We introduce  $\varepsilon$  as a synonym of  $\emptyset$ .

Let  $n$  be a natural number and let  $x, y$  be finite sequences. The functor  $n\text{-BitAdderStr}(x, y)$  yields an unsplit non void strict non empty many sorted signature with arity held in gates and Boolean denotation held in gates and is defined by the condition (Def. 3).

(Def. 3) There exist many sorted sets  $f, g$  indexed by  $\mathbb{N}$  such that

(i)  $n\text{-BitAdderStr}(x, y) = f(n)$ ,

(ii)  $f(0) = 1\text{GateCircStr}(\varepsilon, \text{Boolean}^0 \mapsto \text{false})$ ,

(iii)  $g(0) = \langle \varepsilon, \text{Boolean}^0 \mapsto \text{false} \rangle$ , and

(iv) for every natural number  $n$  and for every non empty many sorted signature  $S$  and for every set  $z$  such that  $S = f(n)$  and  $z = g(n)$  holds  $f(n+1) = S + \text{BitAdderWithOverflowStr}(x(n+1), y(n+1), z)$  and  $g(n+1) = \text{MajorityOutput}(x(n+1), y(n+1), z)$ .

Let  $n$  be a natural number and let  $x, y$  be finite sequences. The functor  $n\text{-BitAdderCirc}(x, y)$  yields a Boolean strict circuit of  $n\text{-BitAdderStr}(x, y)$  with denotation held in gates and is defined by the condition (Def. 4).

(Def. 4) There exist many sorted sets  $f, g, h$  indexed by  $\mathbb{N}$  such that

(i)  $n\text{-BitAdderStr}(x, y) = f(n)$ ,

(ii)  $n\text{-BitAdderCirc}(x, y) = g(n)$ ,

(iii)  $f(0) = 1\text{GateCircStr}(\varepsilon, \text{Boolean}^0 \mapsto \text{false})$ ,

(iv)  $g(0) = 1\text{GateCircuit}(\varepsilon, \text{Boolean}^0 \mapsto \text{false})$ ,

(v)  $h(0) = \langle \varepsilon, \text{Boolean}^0 \mapsto \text{false} \rangle$ , and

(vi) for every natural number  $n$  and for every non empty many sorted signature  $S$  and for every non-empty algebra  $A$  over  $S$  and for every set  $z$  such that  $S = f(n)$  and  $A = g(n)$  and  $z = h(n)$  holds  $f(n+1) = S + \text{BitAdderWithOverflowStr}(x(n+1), y(n+1), z)$  and  $g(n+1) = A + \text{BitAdderWithOverflowCirc}(x(n+1), y(n+1), z)$  and  $h(n+1) = \text{MajorityOutput}(x(n+1), y(n+1), z)$ .

Let  $n$  be a natural number and let  $x, y$  be finite sequences. The functor  $n\text{-BitMajorityOutput}(x, y)$  yielding an element of  $\text{InnerVertices}(n\text{-BitAdderStr}(x, y))$  is defined by the condition (Def. 5).

(Def. 5) There exists a many sorted set  $h$  indexed by  $\mathbb{N}$  such that

(i)  $n\text{-BitMajorityOutput}(x, y) = h(n)$ ,

(ii)  $h(0) = \langle \varepsilon, \text{Boolean}^0 \mapsto \text{false} \rangle$ , and

(iii) for every natural number  $n$  and for every set  $z$  such that  $z = h(n)$  holds  $h(n+1) = \text{MajorityOutput}(x(n+1), y(n+1), z)$ .

The following propositions are true:

(7) Let  $x, y$  be finite sequences and  $f, g, h$  be many sorted sets indexed by  $\mathbb{N}$ . Suppose that

(i)  $f(0) = 1\text{GateCircStr}(\varepsilon, \text{Boolean}^0 \mapsto \text{false})$ ,

(ii)  $g(0) = 1\text{GateCircuit}(\varepsilon, \text{Boolean}^0 \mapsto \text{false})$ ,

(iii)  $h(0) = \langle \varepsilon, \text{Boolean}^0 \mapsto \text{false} \rangle$ , and

(iv) for every natural number  $n$  and for every non empty many sorted signature  $S$  and for every non-empty algebra  $A$  over  $S$  and for every set  $z$  such that  $S = f(n)$  and  $A = g(n)$  and  $z = h(n)$  holds  $f(n+1) = S + \cdot \text{BitAdderWithOverflowStr}(x(n+1), y(n+1), z)$  and  $g(n+1) = A + \cdot \text{BitAdderWithOverflowCirc}(x(n+1), y(n+1), z)$  and  $h(n+1) = \text{MajorityOutput}(x(n+1), y(n+1), z)$ .

Let  $n$  be a natural number. Then  $n\text{-BitAdderStr}(x, y) = f(n)$  and  $n\text{-BitAdderCirc}(x, y) = g(n)$  and  $n\text{-BitMajorityOutput}(x, y) = h(n)$ .

(8) For all finite sequences  $a, b$  holds  $0\text{-BitAdderStr}(a, b) = 1\text{GateCircStr}(\varepsilon, \text{Boolean}^0 \mapsto \text{false})$  and  $0\text{-BitAdderCirc}(a, b) = 1\text{GateCircuit}(\varepsilon, \text{Boolean}^0 \mapsto \text{false})$  and  $0\text{-BitMajorityOutput}(a, b) = \langle \varepsilon, \text{Boolean}^0 \mapsto \text{false} \rangle$ .

(9) Let  $a, b$  be finite sequences and  $c$  be a set. Suppose  $c = \langle \varepsilon, \text{Boolean}^0 \mapsto \text{false} \rangle$ . Then  $1\text{-BitAdderStr}(a, b) = 1\text{GateCircStr}(\varepsilon, \text{Boolean}^0 \mapsto \text{false}) + \cdot \text{BitAdderWithOverflowStr}(a(1), b(1), c)$  and  $1\text{-BitAdderCirc}(a, b) = 1\text{GateCircuit}(\varepsilon, \text{Boolean}^0 \mapsto \text{false}) + \cdot \text{BitAdderWithOverflowCirc}(a(1), b(1), c)$  and  $1\text{-BitMajorityOutput}(a, b) = \text{MajorityOutput}(a(1), b(1), c)$ .

(10) For all sets  $a, b, c$  such that  $c = \langle \varepsilon, \text{Boolean}^0 \mapsto \text{false} \rangle$  holds  $1\text{-BitAdderStr}(\langle a \rangle, \langle b \rangle) = 1\text{GateCircStr}(\varepsilon, \text{Boolean}^0 \mapsto \text{false}) + \cdot \text{BitAdderWithOverflowStr}(a, b, c)$  and  $1\text{-BitAdderCirc}(\langle a \rangle, \langle b \rangle) = 1\text{GateCircuit}(\varepsilon, \text{Boolean}^0 \mapsto \text{false}) + \cdot \text{BitAdderWithOverflowCirc}(a, b, c)$  and  $1\text{-BitMajorityOutput}(\langle a \rangle, \langle b \rangle) = \text{MajorityOutput}(a, b, c)$ .

(11) Let  $n$  be a natural number,  $p, q$  be finite sequences with length  $n$ , and  $p_1, p_2, q_1, q_2$  be finite sequences. Then  $n\text{-BitAdderStr}(p \wedge p_1, q \wedge q_1) = n\text{-BitAdderStr}(p \wedge p_2, q \wedge q_2)$  and  $n\text{-BitAdderCirc}(p \wedge p_1, q \wedge q_1) = n\text{-BitAdderCirc}(p \wedge p_2, q \wedge q_2)$  and  $n\text{-BitMajorityOutput}(p \wedge p_1, q \wedge q_1) = n\text{-BitMajorityOutput}(p \wedge p_2, q \wedge q_2)$ .

(12) Let  $n$  be a natural number,  $x, y$  be finite sequences with length  $n$ , and  $a, b$  be sets. Then  $(n+1)\text{-BitAdderStr}(x \wedge \langle a \rangle, y \wedge \langle b \rangle) = (n\text{-BitAdderStr}(x, y)) + \cdot \text{BitAdderWithOverflowStr}(a, b, n\text{-BitMajorityOutput}(x, y))$  and  $(n+1)\text{-BitAdderCirc}(x \wedge \langle a \rangle, y \wedge \langle b \rangle) = (n\text{-BitAdderCirc}(x, y)) + \cdot \text{BitAdderWithOverflowCirc}(a, b, n\text{-BitMajorityOutput}(x, y))$  and  $(n+1)\text{-BitMajorityOutput}(x \wedge \langle a \rangle, y \wedge \langle b \rangle) = \text{MajorityOutput}(a, b, n\text{-BitMajorityOutput}(x, y))$ .

(13) Let  $n$  be a natural number and  $x, y$  be finite sequences. Then  $(n+1)\text{-BitAdderStr}(x, y) = (n\text{-BitAdderStr}(x, y)) + \cdot \text{BitAdderWithOverflowStr}(x(n+1), y(n+1), n\text{-BitMajorityOutput}(x, y))$  and  $(n+1)\text{-BitAdderCirc}(x, y) = (n\text{-BitAdderCirc}(x, y)) + \cdot \text{BitAdderWithOverflowCirc}(x(n+1), y(n+1), n\text{-BitMajorityOutput}(x, y))$  and  $(n+1)\text{-BitMajorityOutput}(x, y) = \text{MajorityOutput}(x(n+1), y(n+1), n\text{-BitMajorityOutput}(x, y))$ .

(14) For all natural numbers  $n, m$  such that  $n \leq m$  and for all finite sequences  $x, y$  holds  $\text{InnerVertices}(n\text{-BitAdderStr}(x, y)) \subseteq \text{InnerVertices}(m\text{-BitAdderStr}(x, y))$ .

(15) For every natural number  $n$  and for all finite sequences  $x, y$  holds  $\text{InnerVertices}((n+1)\text{-BitAdderStr}(x, y)) = \text{InnerVertices}(n\text{-BitAdderStr}(x, y)) \cup \text{InnerVertices}(\text{BitAdderWithOverflowStr}(x(n+1), y(n+1), n\text{-BitMajorityOutput}(x, y)))$ .

Let  $k, n$  be natural numbers. Let us assume that  $k \geq 1$  and  $k \leq n$ . Let  $x, y$  be finite sequences. The functor  $(k, n)\text{-BitAdderOutput}(x, y)$  yielding an element of  $\text{InnerVertices}(n\text{-BitAdderStr}(x, y))$  is defined by:

(Def. 6) There exists a natural number  $i$  such that  $k = i + 1$  and  $(k, n)\text{-BitAdderOutput}(x, y) = \text{BitAdderOutput}(x(k), y(k), i\text{-BitMajorityOutput}(x, y))$ .

Next we state several propositions:

- (16) For all natural numbers  $n, k$  such that  $k < n$  and for all finite sequences  $x, y$  holds  $(k + 1, n)$ -BitAdderOutput( $x, y$ ) = BitAdderOutput( $x(k + 1), y(k + 1), k$ -BitMajorityOutput( $x, y$ )).
- (17) For every natural number  $n$  and for all finite sequences  $x, y$  holds InnerVertices( $n$ -BitAdderStr( $x, y$ )) is a binary relation.
- (18) For all sets  $x, y, c$  holds InnerVertices(MajorityIStr( $x, y, c$ )) =  $\{\langle\langle x, y \rangle, \&\rangle, \langle\langle y, c \rangle, \&\rangle, \langle\langle c, x \rangle, \&\rangle\}$ .
- (19) For all sets  $x, y, c$  such that  $x \neq \langle\langle y, c \rangle, \&\rangle$  and  $y \neq \langle\langle c, x \rangle, \&\rangle$  and  $c \neq \langle\langle x, y \rangle, \&\rangle$  holds InputVertices(MajorityIStr( $x, y, c$ )) =  $\{x, y, c\}$ .
- (20) For all sets  $x, y, c$  holds InnerVertices(MajorityStr( $x, y, c$ )) =  $\{\langle\langle x, y \rangle, \&\rangle, \langle\langle y, c \rangle, \&\rangle, \langle\langle c, x \rangle, \&\rangle\} \cup \{\text{MajorityOutput}(x, y, c)\}$ .
- (21) For all sets  $x, y, c$  such that  $x \neq \langle\langle y, c \rangle, \&\rangle$  and  $y \neq \langle\langle c, x \rangle, \&\rangle$  and  $c \neq \langle\langle x, y \rangle, \&\rangle$  holds InputVertices(MajorityStr( $x, y, c$ )) =  $\{x, y, c\}$ .
- (22) For all non empty many sorted signatures  $S_1, S_2$  such that  $S_1 \approx S_2$  and InputVertices( $S_1$ ) = InputVertices( $S_2$ ) holds InputVertices( $S_1 + S_2$ ) = InputVertices( $S_1$ ).
- (23) For all sets  $x, y, c$  such that  $x \neq \langle\langle y, c \rangle, \&\rangle$  and  $y \neq \langle\langle c, x \rangle, \&\rangle$  and  $c \neq \langle\langle x, y \rangle, \&\rangle$  and  $c \neq \langle\langle x, y \rangle, \text{xor}\rangle$  holds InputVertices(BitAdderWithOverflowStr( $x, y, c$ )) =  $\{x, y, c\}$ .
- (24) For all sets  $x, y, c$  holds InnerVertices(BitAdderWithOverflowStr( $x, y, c$ )) =  $\{\langle\langle x, y \rangle, \text{xor}\rangle, 2\text{GatesCircOutput}(x, y, c, \text{xor})\} \cup \{\langle\langle x, y \rangle, \&\rangle, \langle\langle y, c \rangle, \&\rangle, \langle\langle c, x \rangle, \&\rangle\} \cup \{\text{MajorityOutput}(x, y, c)\}$ .

One can check that every set which is empty is also non pair.

Observe that  $\emptyset$  is nonpair yielding. Let  $f$  be a nonpair yielding function and let  $x$  be a set. Observe that  $f(x)$  is non pair.

Let  $n$  be a natural number and let  $x, y$  be finite sequences. Note that  $n$ -BitMajorityOutput( $x, y$ ) is pair.

We now state a number of propositions:

- (25) Let  $x, y$  be finite sequences and  $n$  be a natural number. Then  $(n\text{-BitMajorityOutput}(x, y))_1 = \varepsilon$  and  $(n\text{-BitMajorityOutput}(x, y))_2 = \text{Boolean}^0 \mapsto \text{false}$  and  $\pi_1((n\text{-BitMajorityOutput}(x, y))_2) = \text{Boolean}^0$  or  $(n\text{-BitMajorityOutput}(x, y))_1 = 3$  and  $(n\text{-BitMajorityOutput}(x, y))_2 = \text{or}_3$  and  $\pi_1((n\text{-BitMajorityOutput}(x, y))_2) = \text{Boolean}^3$ .
- (26) For every natural number  $n$  and for all finite sequences  $x, y$  and for every set  $p$  holds  $n\text{-BitMajorityOutput}(x, y) \neq \langle p, \&\rangle$  and  $n\text{-BitMajorityOutput}(x, y) \neq \langle p, \text{xor}\rangle$ .
- (27) Let  $f, g$  be nonpair yielding finite sequences and  $n$  be a natural number. Then InputVertices( $(n + 1)$ -BitAdderStr( $f, g$ )) = InputVertices( $n$ -BitAdderStr( $f, g$ ))  $\cup$  (InputVertices(BitAdderWithOverflowStr( $f(n + 1), g(n + 1), n\text{-BitMajorityOutput}(f, g)$ ))  $\setminus$   $\{n\text{-BitMajorityOutput}(f, g)\}$ ) and InnerVertices( $n$ -BitAdderStr( $f, g$ )) is a binary relation and InputVertices( $n$ -BitAdderStr( $f, g$ )) has no pairs.
- (28) For every natural number  $n$  and for all nonpair yielding finite sequences  $x, y$  with length  $n$  holds InputVertices( $n$ -BitAdderStr( $x, y$ )) =  $\text{rng } x \cup \text{rng } y$ .
- (29) Let  $x, y, c$  be sets,  $s$  be a state of MajorityCirc( $x, y, c$ ), and  $a_1, a_2, a_3$  be elements of *Boolean*. If  $a_1 = s(\langle\langle x, y \rangle, \&\rangle)$  and  $a_2 = s(\langle\langle y, c \rangle, \&\rangle)$  and  $a_3 = s(\langle\langle c, x \rangle, \&\rangle)$ , then (Following( $s$ ))(MajorityOutput( $x, y, c$ )) =  $a_1 \vee a_2 \vee a_3$ .
- (30) Let  $x, y, c$  be sets. Suppose  $x \neq \langle\langle y, c \rangle, \&\rangle$  and  $y \neq \langle\langle c, x \rangle, \&\rangle$  and  $c \neq \langle\langle x, y \rangle, \&\rangle$  and  $c \neq \langle\langle x, y \rangle, \text{xor}\rangle$ . Let  $s$  be a state of MajorityCirc( $x, y, c$ ). Then Following( $s, 2$ ) is stable.

- (31) Let  $x, y, c$  be sets. Suppose  $x \neq \langle \langle y, c \rangle, \& \rangle$  and  $y \neq \langle \langle c, x \rangle, \& \rangle$  and  $c \neq \langle \langle x, y \rangle, \& \rangle$  and  $c \neq \langle \langle x, y \rangle, \text{xor} \rangle$ . Let  $s$  be a state of  $\text{BitAdderWithOverflowCirc}(x, y, c)$  and  $a_1, a_2, a_3$  be elements of  $\text{Boolean}$ . Suppose  $a_1 = s(x)$  and  $a_2 = s(y)$  and  $a_3 = s(c)$ . Then  $(\text{Following}(s, 2))(\text{BitAdderOutput}(x, y, c)) = a_1 \oplus a_2 \oplus a_3$  and  $(\text{Following}(s, 2))(\text{MajorityOutput}(x, y, c)) = a_1 \wedge a_2 \vee a_2 \wedge a_3 \vee a_3 \wedge a_1$ .
- (32) Let  $x, y, c$  be sets. Suppose  $x \neq \langle \langle y, c \rangle, \& \rangle$  and  $y \neq \langle \langle c, x \rangle, \& \rangle$  and  $c \neq \langle \langle x, y \rangle, \& \rangle$  and  $c \neq \langle \langle x, y \rangle, \text{xor} \rangle$ . Let  $s$  be a state of  $\text{BitAdderWithOverflowCirc}(x, y, c)$ . Then  $\text{Following}(s, 2)$  is stable.
- (33) Let  $n$  be a natural number,  $x, y$  be nonpair yielding finite sequences with length  $n$ , and  $s$  be a state of  $n\text{-BitAdderCirc}(x, y)$ . Then  $\text{Following}(s, 1 + 2 \cdot n)$  is stable.
- (34) Let  $i$  be a natural number and  $x$  be a finite sequence with length  $i + 1$ . Then there exists a finite sequence  $y$  with length  $i$  and there exists a set  $a$  such that  $x = y \hat{\ } \langle a \rangle$ .
- (35) For all finite sequences  $p, q$  holds  $(p \hat{\ } q) \upharpoonright \text{dom } p = p$ .
- (36) Let  $i$  be a natural number and  $x$  be a nonpair yielding finite sequence with length  $i + 1$ . Then there exists a nonpair yielding finite sequence  $y$  with length  $i$  and there exists a non pair set  $a$  such that  $x = y \hat{\ } \langle a \rangle$ .
- (37) For every natural number  $n$  there exists a function  $N$  from  $\mathbb{N}$  into  $\mathbb{N}$  such that  $N(0) = 1$  and  $N(1) = 2$  and  $N(2) = n$ .

## REFERENCES

- [1] Grzegorz Bancerek. Cardinal numbers. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Voll/card\\_1.html](http://mizar.org/JFM/Voll/card_1.html).
- [2] Grzegorz Bancerek. The fundamental properties of natural numbers. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Voll/nat\\_1.html](http://mizar.org/JFM/Voll/nat_1.html).
- [3] Grzegorz Bancerek. Curried and uncurried functions. *Journal of Formalized Mathematics*, 2, 1990. [http://mizar.org/JFM/Vol2/funct\\_5.html](http://mizar.org/JFM/Vol2/funct_5.html).
- [4] Grzegorz Bancerek and Krzysztof Hryniewiecki. Segments of natural numbers and finite sequences. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Voll/finseq\\_1.html](http://mizar.org/JFM/Voll/finseq_1.html).
- [5] Grzegorz Bancerek and Yatsuka Nakamura. Full adder circuit. Part I. *Journal of Formalized Mathematics*, 7, 1995. [http://mizar.org/JFM/Vol7/facirc\\_1.html](http://mizar.org/JFM/Vol7/facirc_1.html).
- [6] Grzegorz Bancerek, Shin'nosuke Yamaguchi, and Yasunari Shidama. Combining of multi cell circuits. *Journal of Formalized Mathematics*, 14, 2002. <http://mizar.org/JFM/Vol14/circcmb2.html>.
- [7] Czesław Byliński. Functions and their basic properties. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Voll/funct\\_1.html](http://mizar.org/JFM/Voll/funct_1.html).
- [8] Czesław Byliński. Functions from a set to a set. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Voll/funct\\_2.html](http://mizar.org/JFM/Voll/funct_2.html).
- [9] Czesław Byliński. Partial functions. *Journal of Formalized Mathematics*, 1, 1989. <http://mizar.org/JFM/Voll/partfun1.html>.
- [10] Czesław Byliński. Finite sequences and tuples of elements of a non-empty sets. *Journal of Formalized Mathematics*, 2, 1990. [http://mizar.org/JFM/Vol2/finseq\\_2.html](http://mizar.org/JFM/Vol2/finseq_2.html).
- [11] Czesław Byliński. The modification of a function by a function and the iteration of the composition of a function. *Journal of Formalized Mathematics*, 2, 1990. [http://mizar.org/JFM/Vol2/funct\\_4.html](http://mizar.org/JFM/Vol2/funct_4.html).
- [12] Yatsuka Nakamura and Grzegorz Bancerek. Combining of circuits. *Journal of Formalized Mathematics*, 7, 1995. <http://mizar.org/JFM/Vol7/circcomb.html>.
- [13] Yatsuka Nakamura, Piotr Rudnicki, Andrzej Trybulec, and Pauline N. Kawamoto. Preliminaries to circuits, II. *Journal of Formalized Mathematics*, 6, 1994. <http://mizar.org/JFM/Vol6/msafree2.html>.
- [14] Yatsuka Nakamura, Piotr Rudnicki, Andrzej Trybulec, and Pauline N. Kawamoto. Introduction to circuits, II. *Journal of Formalized Mathematics*, 7, 1995. <http://mizar.org/JFM/Vol7/circuit2.html>.
- [15] Takaya Nishiyama and Yasuho Mizuhara. Binary arithmetics. *Journal of Formalized Mathematics*, 5, 1993. <http://mizar.org/JFM/Vol5/binarith.html>.
- [16] Andrzej Trybulec. Enumerated sets. *Journal of Formalized Mathematics*, 1, 1989. <http://mizar.org/JFM/Voll/enumset1.html>.
- [17] Andrzej Trybulec. Tarski Grothendieck set theory. *Journal of Formalized Mathematics*, Axiomatics, 1989. <http://mizar.org/JFM/Axiomatics/tarski.html>.

- [18] Andrzej Trybulec. Tuples, projections and Cartesian products. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Vol1/mcart\\_1.html](http://mizar.org/JFM/Vol1/mcart_1.html).
- [19] Andrzej Trybulec. Many-sorted sets. *Journal of Formalized Mathematics*, 5, 1993. <http://mizar.org/JFM/Vol5/pboole.html>.
- [20] Andrzej Trybulec. Many sorted algebras. *Journal of Formalized Mathematics*, 6, 1994. [http://mizar.org/JFM/Vol6/msualg\\_1.html](http://mizar.org/JFM/Vol6/msualg_1.html).
- [21] Andrzej Trybulec. Subsets of real numbers. *Journal of Formalized Mathematics*, Addenda, 2003. <http://mizar.org/JFM/Addenda/numbers.html>.
- [22] Zinaida Trybulec. Properties of subsets. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Vol1/subset\\_1.html](http://mizar.org/JFM/Vol1/subset_1.html).
- [23] Edmund Woronowicz. Relations and their basic properties. *Journal of Formalized Mathematics*, 1, 1989. [http://mizar.org/JFM/Vol1/relat\\_1.html](http://mizar.org/JFM/Vol1/relat_1.html).
- [24] Edmund Woronowicz. Many-argument relations. *Journal of Formalized Mathematics*, 2, 1990. <http://mizar.org/JFM/Vol2/margrell.html>.

*Received March 22, 2002*

*Published January 2, 2004*

---